WWW.INFOPULSAS.LT info@infopulsas.lt

AirLink® LX40: LTE Router

The AirLink® LX40 is a compact LTE router offering "out-of-the box" LTE and Wi-Fi connectivity that is simple to install. The LX40 supports security, digital signage and loT applications in fixed, protected environments.



AirLink® LX40

Ultra Compact LTE Commercial Router for Security Cameras, Digital Signage, IoT, and Small Business









AirLink® LX40 - Router Specifications

| North America | ЕМЕА | Australia & New Zealand |
|--|--|--|
| | | |
| Up to 150 Mbps, Cat-4 (WP7610) | Up to 150 Mbps, Cat-4 (WP7607) | Up to 150 Mbps, Cat-4 (WP7609) |
| Up to 50 Mbps | Up to 50 Mbps | Up to 50 Mbps |
| | | |
| B1, B4, B5, B12, B13, B14, B17, B66 | B1, B3, B7, B8, B20, B28 | B1, B3, B5, B7, B8, B28 |
| | | |
| B2, B4, B5 | B1, B8 | B1, B5, B8 |
| | | |
| | 900, 1800 | |
| | Up to 150 Mbps, Cat-4 (WP7610) Up to 50 Mbps B1, B4, B5, B12, B13, B14, B17, B66 | Up to 150 Mbps, Cat-4 (WP7610) Up to 50 Mbps Up to 50 Mbps Up to 50 Mbps B1, B4, B5, B12, B13, B14, B17, B66 B2, B4, B5 B1, B8 |

Approvals

| HOST INTERFACES | | | |
|-----------------|-------------------------|------------------------------|------------------------------|
| Part Numbers | 1104579, 1104573 (WiFi) | 1104181, 1104182 (Wi- Fi) | 1104183, 1104184 (Wi- Fi) |
| Part Numbers | | | |
| Carrier | AT&T, Verizon, T-Mobile | | |
| Regulatory | FCC, IC, PTCRB | GCF, CE | GCF, RCM |

1 Gigabit RJ-45 Ethernet Port (POE) USB 2.0 Micro-B Connector

2 SMA antenna connectors (cellular, diversity)

1 RP SMA antenna connector (Wi-Fi)

SECURITY

Remote Authentication (LDAP, RADIUS, TACACS+) DMZ Inbound and Outbound Port filtering Inbound and Outbound Trusted IP MAC Address Filtering PCI compatible Secure Firmware Update

WI-FI (OPTIONAL)

Dual Band 2.4/5GHz Wi-Fi 802.11 b/g/n/ac (Wave2 Client Mode) Support for 10 clients, WPA2 Enterprise Output power 16dBm per channel Access Point or Client Mode (Wi-Fi as WAN) Single SSID Support Captive Portal

LAN (ETHERNET/USB)

DHCP Server IP Passthrough VLAN Host Interface Watchdog PPPoE

ENVIRONMENTAL

| Operating Temperature | -20°C to +65°C / -4°F to +149°F (+60°C / +140°F when using PoE) |
|-----------------------|---|
| Storage Temperature | -40°C to +85°C / -40°F to +185°F |
| Humidity | 90% RH @ 60°C |
| | Military Spec MIL-STD-810G conformance to shock, vibration, thermal shock, and humidity IP21 rated ingress protection |

POWER

| POWER | |
|-------------------------|--|
| Input/Operating Voltage | 7 to 36 VDC |
| Power Modes | Low voltage disconnect to prevent battery drain Built-in protection against voltage transients Power-over-Ethernet (PoE) powered device Ignition Sense with time delay shutdown |
| INPUT/OUTPUT | |
| | Configurable I/O pin on power connector Digital Inputs: ON Voltage: 2.7 to 36 VDC Configurable Pull-ups for dry contact input Digital Open Collector Output > sinking 500 mA Analog Inputs: 0.5-36VDC (range selectable) |
| NETWORK AND ROUTING | |
| | Network Address Translation (NAT) Reliable Static Route Port Forwarding Dynamic DNS Policy Routing Verizon PNTM NEMO/DMNR IPV6 Gateway VRRP |
| VPN | |
| | IPsec, GRE, and OpenVPN Client Up to 5 concurrent tunnels Split Tunnel Dead Peer Detection (DPD) |
| ROUTER MANAGEMENT IN | TERFACES |
| | Local web user interface AT Command Line Interface (Telnet/SSH) SNMP SMS Commands |
| APPLICATION FRAMEWORK | (|

ALEOS Application Framework (AAF) LUA Scripting Language

EVENTS ENGINE

| | Custom event triggers and reports Configurable interface, no programming |
|---------------|--|
| Event Types | Digital Input, Network Parameters, Data Usage, Timer, Power, Device Temperature and Voltage |
| Report Types | RAP, SMS, Email, SNMP Trap, TCP (Binary, XML, CSV) |
| Event Actions | Drive Relay Output |

INDUSTRY CERTIFICATIONS

| Safety | IECEE Certification Bodies Scheme (CB Scheme), UL 60950 |
|---------------|---|
| Vehicle Usage | E-Mark (UN ECE Regulation 10.04), ISO7637-2, SAE J1455 (Shock, Vibration, Electrical) |
| Environments | RoHS2, REACH, WEEE |
| Public Safety | FirstNet® |

SUPPORT AND WARRANTY

1 year standard warranty with up to 5 years extended warranty with current AirLink Complete subscription. Unrestricted critical firmware updates.

ACCESSORIES


| In The Box | LX40, DC Power Cable and Quick Start Guide |
|-------------------------------------|--|
| Other Accessories (sold separately) | 2000579 AC Adapter, 12VDC 6001221 DIN Rail Bracket 6001110 Cellular Paddle Antenna 6001111 Wi-Fi 2.4/5Hz Paddle Antenna For antenna options visit: sierrawireless.com/antennas |
| | |

CONSTRUCTION

Polycarbonate housings that meet MIL-810/IP21 environmental standards.

DIMENSIONS

103 mm (111 mm including connectors) x 79 mm x 25 mm 4.1 in (4.4 in including connectors) x 3.1 in x 1.0 in Weight: 250g



*For carrier specific band support please refer to the hardware user guide.